To communicate to the EDU, (Electronic Disply Unit).

- 1) Connect the cable, marked 'EDI', in back of the IBM computer, COM1.
- 2) To get to the Root Directory, Type "CD..".
- 3) Change Directory to EDU.
- 4) Type "Dir".
- 5) Run "RCA.Exe".
- 6) Set up parameters.

Baud Rate: 1200 Data Bits: 8
Parity: None Stop Bits: 1
(Note: Use arrow keys to make selections)

- 7) Type "Enter" when finished
- 8) From Main Menu Select '#4'.

Note: \triangle = Control, & \triangle D = Control pressed while simultaneously pressing D.

To change TEXT in Unit 3.....

- 1) To type in a Message --- Begin with $\triangle D \triangle S$.
- 2) Message up 20 characters.
- 3) End with $^{\wedge}$ R.
- 4) Push the "END" key.

(Note: Be sure the "Number Lock" isn't selected, or the "END" key won't work)

To Change DATE or Time in Unit 1.....

- 1) To Change the Time --- Begin with $\land V \land V$
- 2) Followed with... h1, h2, m1, m2, s1, s2,

Where h1 = tens of hours (24 hour format)
h2 = ones of hours
m1 = tens of minutes
m2 = ones of minutes
s1 = tens of seconds
s2 = ones of seconds

- 3) End with R R .
- 1) To Change the Date --- Begin with AV C C
- 2) Followed with... d1, d2, d3, m1, m2, y1, y2,

Where d1 = day of the week (sun=1, mon=2. etc.)

d2 = tens of day of the month

d3 = ones of day of the month

m1 = tens of month

m2 = ones of month

y1 = tens of years

y2 = ones of years

- 3) End with $\triangle R \triangle R$.
- 4) Push the "END" key.

(Note: Be sure the "Number Lock" isn't selected, or the "END" key won't work)

8) Remove the Cable "EDI" and replace the plug that was in `Com1'.